



<b>Motorcycle Manufacturer</b>	<b>aprilia</b>
<b>Model</b>	<b>SCARABEO 100 cc</b>
<b>Year</b>	<b>//</b>
<b>Issue</b>	<b>02/2000 – rev. 00</b>

<b>Recommended siting</b>	Behind the front shield.
<b>Power supply</b>	Connect the positive supply wire of the alarm system to the ORANGE wire and the negative supply wire of the alarm system to the BLUE wire. These wires are found in the 4-way connector available on the loom coming out of the ignition lock.
<b>Engine immobilisation (1)</b>	Follow Diagram B. Cut the GREEN wire available in the 4-way connector on the loom coming out of the ignition lock.
<b>Engine immobilisation (2)</b>	Cut the YELLOW/RED wire available in the 9-way connector, placed under the ignition lock.
<b>Ignition controlled positive supply</b>	Connect to the GREEN wire available in the 4-way connector of the loom coming out of the ignition lock (the same wire as used for engine immobilisation 1).
<b>Turn indicators</b>	Connect to the LIGHT BLUE wire and RED wire of the front turn indicators available in the 9-way connector, placed under the ignition lock.