

Motorcycle Manufacturer	aprilia
Model	TUONO 125 cc
Year	
Issue	11/03 Rev. 00

Recommended siting	Under the tank, over the battery, behind the steering post.
Power supply	Connect the positive and negative supply wires of the security system to the positive and negative terminals of the motorcycle battery.
Engine immobilisation (1)	Follow diagram B. Cut the GREY/RED wire found in the round individual connector of the harness that is secured to the frame on the right of the battery, under the fuel tank.
Engine immobilisation (2)	Cut the YELLOW/RED wire found in the white 6-way connector of the harness that is secured to the frame on the right of the battery, under the fuel tank.
Ignition controlled positive supply	Connect to the YELLOW wire found in the white 6-way connector of the harness that is secured to the frame on the right of the battery, under the fuel tank.
Turn indicators	Connect to the LIGHT BLUE and RED wires found in the white 9-way connector of the harness that is secured to the frame on the right of the battery, under the fuel tank.

To avoid backfeeds through the turn indicators, it is recommended to fit a diode to the GREEN wire found in the 2-way plug that is connected to the flasher unit, under the rear seat on the right side.

