



Motorcycle Manufacturer	Kawasaki
Model	ZX6R
Issue	11/96 – rev. 00

- Recommended siting** Under the seat, behind the battery.
- Power supply** Connect the positive and the negative supply wires of the alarm system to the motorcycle battery.
- Engine immobilisation (1)** Follow Diagram A. Connect to the GREEN wire of the black 8-way connector of the ignition unit available behind the right side rear panel.
- Engine immobilisation (2)** Follow Diagram B. Cut the YELLOW/RED wire in the red 4-way connector of the solenoid placed behind the battery.
- Ignition controlled positive supply** Connect to the RED/WHITE wire of the 2-way connector of the rear stop light switch, available on the right side of the battery.
- Turn indicators** Connect to the GREEN and GREY wires of the rear turn indicators.