



Motorcycle Manufacturer	Kawasaki
Model	ZX7R
Issue	11/96 – rev. 00

Recommended siting	Behind the left side rear panel.
Power supply	Connect the positive and the negative supply wires of the alarm system to the motorcycle battery.
Engine immobilisation (1)	Follow diagram A. Connect to the BLACK/WHITE wire of the connector of the ignition unit behind the right side rear panel.
Engine immobilisation (2)	Follow diagram B. Cut the YELLOW/RED wire in the red 4-way connector of the starter solenoid behind the battery.
Ignition controlled positive supply	Connect to the RED/WHITE wire in the 2-way connector of the harness of the rear stop light switch available on the right of the battery
Turn indicators	Connect to the GREEN and GREY wires of the rear turn indicators.