



Motorcycle Manufacturer	<i>Malaguti</i>
Model	SPIDERMAX 500 cc
Issue	03/05 Rev. 00

Recommended siting	Under the front shield, between the headlamps.
Power supply	Connect the positive supply wire of the alarm system to the RED/BLUE wire found in the connector that is attached to the instrument panel. Connect the negative supply wire of the alarm system to an earth point on the bike frame.
Engine immobilisation (1)	Follow diagram B. Cut the BROWN/WHITE wire available in the black 6-way connector under the plastic cover of the handle-bar.
Engine immobilisation (2)	Cut the RED/WHITE wire available in the black 6-way connector under the plastic cover of the handle-bar.
Ignition controlled positive supply	
Turn indicators	