


Motorcycle Manufacturer	 PIAGGIO
Model	BEVERLY 125-200
Issue	01/03 – rev. 00

Recommended siting	Behind the front shield.
Power supply	Connect the positive supply wire of the alarm unit to the RED/BLACK wire found in the 4-way white plug that is connected to the ignition lock. Connect the negative supply wire of the alarm unit to the screw of the bracket holding the immobiliser unit.
Engine immobilisation (1)	Follow diagram B. Cut the WHITE or ORANGE wire found in the 4-way white connector that is plugged to the ignition lock.
Engine immobilisation (2)	Cut the GREEN/BLACK wire found in the harness that comes down from the handle-bar next to the steering post.
Ignition controlled positive supply	Connect to the WHITE or ORANGE wire that is used for engine immobilisation 1, in the 4-way white plug that is connected to the ignition lock.
Turn indicators	Connect to the PINK and BLUE/WHITE wires found in the 6-way white connector that is plugged into the headlamp.